



X5 - RUGGED BATTERY EXPANSION PACK



EXTENDED POWER ANYWHERE

The X5 is designed to deploy quickly and connect easily to the R5, enabling extended clean power anywhere. Its rugged design and high portability make it ideal to extend the R5 run time during grid outages, remote production, off-grid events, and critical disaster response.

CAPABILITIES



Recharge X5 directly from R5



Simple plug-and-play connection to R5



Rugged and weatherized case (IP67)



Portable with wheels + handles



Energy monitoring via Bluetooth app



5kWh capacity extends R5 run time by 2x

RUGGED AND MOBILE

The X5 is ready to extend power to devices powered by the R5 including:



Tools



Lights



Laptops



Pumps



Phones



Refrigerators

EXTENDED

The X5 is the battery expansion pack to the R5. A simple plug-and-play connection it to the R5 allows one X5 to double (2x) the R5 run time.

POWER

The X5 has 5kWh energy capacity that is instantly available as soon as it is connected to the R5. Multiple X5 can be connected to a R5 or other X5s for virtually unlimited energy.

ANYWHERE

The X5 is ruggedized for indoor/outdoor use and equipped with wheels and handles for easy transportation and full mobility.





X5 - RUGGED BATTERY EXPANSION PACK

PRODUCT SPECIFICATION

This product must be maintained and utilized within the environmental conditions and operating limits specified below. Any applicable product warranty shall become null and void if product is subjected to and/or operated outside of these limits. Specifications are subject to change without notice.

Performance, Physical, and Environmental	
Model	X5
Nameplate Capacity	5.12 kWh (100 Ah)
Usable Capacity	5.0 kWh (100%)
Voltage	48V
Maximum Cycles	7,000 cycles
Weight	47.3 kg / 104 lbs
Dimensions	61.6 x 49.6 x 31.2 cm / 24.3 x 19.5 x 12.3 in
Ingress Protection	IP67
Operating Temperature Limits	Charging: 0 – 40°C / 32 – 104°F Discharging: -20 - 45°C / -4 - 113°F
Expandable Capacity	Connect to a R5 or another X5 in parallel
Connector Type	Anderson Powerpole

